



SOLUTIONS FOR ALL YOUR APPLICATIONS

Stock No.
5750/5770/5780
User Manual

ACA Series

Apartment Complex Amplifiers with Passive Return Path

Model	Stock No.
ACA-30-55R	5750
ACA-30-75R	5770
ACA-30-86R	5780



DESCRIPTION

The Blonder Tongue two-way Apartment Complex Amplifiers with Passive Return Path are broadband indoor hybrid distribution amplifiers designed for RF distribution systems whose input signal source is a "cable drop", the output of an MATV headend or a small CATV headend. Three models are available: The #5750 with a 47 to 550 MHz bandpass, the #5770 with a 47 to 750 MHz bandpass, and the #5780 with a 47 to 860 MHz bandpass.

All amplifiers are designed for apartment housing complex, hospital, prison or hotel applications. They have flat operational gain of 31 dB with 15 dB of variable gain control range and 10 dB of variable slope control. Using a push-pull hybrid module as its gain block, they will deliver high output level signals with low distortion.

The unit is powered via an external AC/DC adapter.

FEATURES

- Hybrid IC Circuitry for High Output with Low Distortion
- Exceptional Temperature Stability Range of -20° C to +60° C
- 5-30 MHz return bandwidth
- Low 47 MHz Forward Band Edge
- Line Transient Protection
- Externally Accessible Gain and Slope Controls for Easy Adjustments

800-523-6049
www.blondertongue.com

Made in China

651170200J
112816

The lightning flash with arrowhead symbol within an equilateral triangle is intended to alert you to the presence of uninsulated "dangerous voltage" within the product's enclosure that may be of sufficient magnitude to constitute a risk of electrical shock to persons.



CAUTION
RISK OF ELECTRIC SHOCK
DO NOT OPEN



The exclamation point within an equilateral triangle is intended to alert you to the presence of important operating and maintenance (servicing) instructions in the literature accompanying the product.

**TO REDUCE THE RISK OF ELECTRICAL SHOCK, DO NOT REMOVE COVER FROM THIS UNIT.
NO USER-SERVICEABLE PARTS INSIDE. REFER SERVICING TO QUALIFIED SERVICE PERSONNEL.**

WARNING: TO PREVENT SHOCK HAZARD, DO NOT EXPOSE THIS UNIT TO RAIN OR MOISTURE

NOTE TO CATV INSTALLERS

This reminder is provided to call the CATV System Installer's attention to Article 820-40 of the NEC that provides guidelines for proper grounding and, in particular, specifies that the cable ground shall be connected to the grounding system of the building, as close to the point of cable entry as practical.

Model: Stock No:	ACA-30-55R 5750	ACA-30-75R 5770	ACA-30-86R 5780
RF			
Frequency Range (MHz):	5-30 47-550 MHz	5-30 47-750 MHz	5-30 47-860 MHz
Channel Loading:	77	110	129
Flatness (dB):	±1.00	±1.00	±1.00
Gain (Reverse) (dB):	31, (-.75)	31, (-.75)	31, (-.75)
Noise Figure (dB) (a):	8.5	9.0	9.0
Output Level (dBmV):	+36/+44	+34/+44	+34/+44
Gain Control Range (dB):	15	15	15
Slope Control Range (dB):	10	10	10
Composite Triple Beat - CTB (dB) (b):	-64	-63	-56
Cross Modulation - XMOD (dB) (b):	-64	-62	-58
Composite Second Order - CSO (dB) (b):	-58	-64	-58
Hum Modulation (dB):	-65	-65	-65
Input Return Loss (dB):	12	12	12
Output Return Loss (dB):	12	12	12
General			
Power Input: (ext AC/DC adapter) Output:	100-240 VAC 50/60 Hz 0.6A 24VDC 1000mA		
Operating Temperature Range:	-20 to +60		
Mechanical			
Dimensions (LxWxH):	6.3" x 8.86" x 2.76" in (160 mm x 225 mm x 70 mm)		
Weight:	3.7 lbs (1.7kg)		

Notes: (a) Measured at full gain with 0dB slope. (b) At rated output capability and channel loading.

INSTALLATION PRECAUTIONS TABLE

PRECAUTION	REQUIREMENT
Ensure easy access to rack wiring	Allow a minimum of 18 in. (50 cm) clearance behind the equipment rack(s).
Facilitate servicing and maintenance	Allow a minimum of 36 in. (100 cm) clearance in front of equipment rack(s).
Avoid direct heating or air conditioning	If unavoidable, use deflector plates.
AC power source outlets	Locate equipment near sufficient outlets to provide power for test equipment and power tools.
Rack support	Make certain rack supports are sufficiently rigid to support rack(s).
Building leakage	Beware of dripping water onto equipment from leaky roofs, waveguide roof entries, and cold water pipe condensations.

Returning Product for Repair (or Credit)

A Return Material Authorization (RMA) Number is required on all products returned to Blonder Tongue, regardless if the product is being returned for repair or credit. Before returning product, please contact the Blonder Tongue Service Department at 1-800-523-6049, Ext. 4256 or visit our website: www.blondertongue.com for further information.